



- NOTES:
- UNLESS OTHERWISE NOTED, ALL SWITCHES ARE SHOWN AT 25°C (77°F), AT ATMOSPHERIC PRESSURE, AT 50% RELATIVE HUMIDITY, WITH ALL UTILITIES TURNED OFF, AND AFTER A NORMAL SHUTDOWN HAS OCCURRED.
  - DASHED LINES INDICATE RECOMMENDED FIELD WIRING BY OTHERS. DASHED LINE ENCLOSURES AND/OR DASHED DEVICE OUTLINES INDICATE COMPONENTS PROVIDED BY THE FIELD. PHANTOM LINE ENCLOSURES INDICATE ALTERNATE CIRCUITRY OR AVAILABLE SALES OPTIONS. SOLID LINE INDICATES WIRING BY TRANE CO.
  - NUMBERS ALONG THE RIGHT SIDE OF THE SCHEMATIC DESIGNATE THE LOCATION OF CONTACTS BY LINE NUMBER. AN UNDERLINED NUMBER INDICATES A NORMALLY CLOSED CONTACT, AN OPEN ARROWHEAD BELOW THE LINE NUMBER POINTING UPWARD INDICATES A TIMED CONTACT WHICH BEGINS TIMING WHEN ENERGIZED.
- 4 SEE APPLICABLE HEATING SECTION DIAGRAM FOR BALANCE OF CIRCUIT.
  - 6 460V/60HZ TRANSFORMER SHOWN. SEE INSET "1A" 575/60HZ CONNECTIONS.
  - 12 460V/60HZ TRANSFORMERS SHOWN. SEE INSET "1B" FOR 575V/60HZ CONNECTIONS.
  - 13 460V/60HZ TRANSFORMER SHOWN. SEE INSET "1C" FOR 575/60HZ TRANSFORMER.
  - 14 SEE APPLICABLE VARIABLE FREQUENCY DRIVE DIAGRAM FOR BALANCE OF CIRCUIT.

DEVICE DESIGN	DESCRIPTION	LINE NUMBER
1K10	CONTACTOR - CONDENSER FAN	155
1K113	CONTACTOR - COMPRESSOR	134
1K114	CONTACTOR - COMPRESSOR	149
1K17	CONTACTOR - EXHAUST FAN	98
1K5	CONTACTOR - COMPRESSOR	136
1K6	CONTACTOR - COMPRESSOR	151
1K7	CONTACTOR - CONDENSER FAN	138
1K8	CONTACTOR - CONDENSER FAN	140
1K9	CONTACTOR - CONDENSER FAN	153

DEVICE DESIGN	DESCRIPTION
1TB4, 1TB5, 1TB16, 1TB17	CONTROLS - CUSTOMER CONNECTIONS
1TB6-1TB10	CONTROLS - FACTORY
4TB2	POWER - ELECTRIC HEAT OPTION
4TB3	CONTROLS - ELECTRIC HEAT
4TB14, 4TB15	CONTROLS - GAS HEAT

LEGEND	LINE NUMBER	
1CB11	CIRCUIT BREAKER - COMPRESSOR	31
1CB14	CIRCUIT BREAKER - COMPRESSOR	16
1CB15	CIRCUIT BREAKER - COMPRESSOR	26
1CB2	CIRCUIT BREAKER - EXHAUST FAN	29
1CB9	CIRCUIT BREAKER - COMPRESSOR	21
1F1	FUSE - CONDENSER FAN	36
1F2	FUSE - CONDENSER FAN	36
1F3	FUSE - CONDENSER FAN	36
1F4	FUSE - CONDENSER FAN	36
1F5	FUSE - CONDENSER FAN	36
1F55	FUSE - CONVENIENCE OUTLET	13
1F56	FUSE - CONVENIENCE OUTLET	13
1F57	FUSE - SUPPLY FAN V.F.D.	30
1F58	FUSE - SUPPLY FAN V.F.D.	30
1F59	FUSE - SUPPLY FAN V.F.D.	30
1F6	FUSE - CONDENSER FAN	36
1F60	FUSE - SUPPLY FAN V.F.D.	30
1F61	FUSE - SUPPLY FAN V.F.D.	30
1F62	FUSE - SUPPLY FAN V.F.D.	30
1F7	FUSE - CONTROL CIRCUIT	56
1F72	FUSE - TRANSFORMER CIRCUIT	36
1F73	FUSE - TRANSFORMER CIRCUIT	36
1F74	FUSE - TRANSFORMER CIRCUIT	36
1K10	CONTACTOR - CONDENSER FAN	40
1K113	CONTACTOR - COMPRESSOR	14, 15, 16, 17
1K114	CONTACTOR - COMPRESSOR	24, 25, 26, 27
1K17	CONTACTOR - EXHAUST FAN	25
1K5	CONTACTOR - COMPRESSOR	19, 20, 21, 22
1K6	CONTACTOR - COMPRESSOR	29, 30, 31, 32
1K7	CONTACTOR - CONDENSER FAN	40
1K8	CONTACTOR - CONDENSER FAN	40
1K9	CONTACTOR - CONDENSER FAN	40
1S1	SWITCH - CONTROL CIRCUIT	56
1S14/1TB1	MANUAL DISCONNECT/TERM BLOCK	19
1S70	SWITCH - 24V TRANSFORMER	56
1S74	SWITCH - CONV. OUTLET	10
1T1	TRANSFORMER - CONTROL POWER	55
1T2	TRANSFORMER - 24 VAC	53
1T3	TRANSFORMER - 24 VAC	53
1T4	TRANSFORMER - 24 VAC	53
1U126	OVERLOAD-EXHAUST-FAN	23
2B1	MOTOR - CONDENSER FAN	48
2B13	MOTOR - CONDENSER FAN	48
2B14	MOTOR - CONDENSER FAN	48
2B15	MOTOR - CONDENSER FAN	48
2B17	COMPRESSOR	22
2B17HR13	HEATER - CRANKCASE	19
2B18	COMPRESSOR	32
2B18HR15	HEATER - CRANKCASE	29
2B19	MOTOR - CONDENSER FAN	48
2B2	MOTOR - CONDENSER FAN	48
2B20	MOTOR - CONDENSER FAN	48
2B21	MOTOR - CONDENSER FAN	48
2B27	COMPRESSOR	17
2B27HR16	HEATER - CRANKCASE	14
2B28	COMPRESSOR	27
2B28HR17	HEATER - CRANKCASE	24
2B3	MOTOR - CONDENSER FAN	48
2B4	MOTOR - CONDENSER FAN	48
2B5	MOTOR - CONDENSER FAN	48
2B6	MOTOR - CONDENSER FAN	48
2J1	RECEPTACLE - CONV. OUTLET	4
2T16	TRANSFORMER - CONV. OUTLET	8
3B10	MOTOR - EXHAUST FAN	22
3B12	MOTOR - SUPPLY FAN	22
3B9	MOTOR - SUPPLY FAN	22
3U72	V.F.D. - SUPPLY FAN	24
3U73	V.F.D. - SUPPLY FAN	24

AREA	LOCATION
1	INSIDE UNIT CONTROL BOX
2	CONDENSER SECTION
3	AIR HANDLER SECTION
4	HEATING SECTION
5	EXTERNAL FIELD MTD DEVICE

**CAUTION**  
USE COPPER CONDUCTORS ONLY!  
UNIT TERMINALS ARE NOT DESIGNED TO ACCEPT OTHER TYPES OF CONDUCTORS.  
FAILURE TO DO SO MAY CAUSE DAMAGE TO THE EQUIPMENT.

**ATTENTION**  
N'UTILISER QUE DES CONDUCTEURS EN CUIVRE!  
LES BORNES DE L'UNITÉ NE SONT PAS CONÇUES POUR RECEVOIR D'AUTRES TYPES DE CONDUCTEURS.  
L'UTILISATION DE TOUT AUTRE CONDUCTEUR PEUT ENDOMMAGER L'EQUIPEMENT.

**PRECAUCIÓN**  
¡UTILICE ÚNICAMENTE CONDUCTORES DE COBRE!  
LAS TERMINALES DE LA UNIDAD NO ESTÁN DISEÑADAS PARA ACEPTAR OTROS TIPOS DE CONDUCTORES.  
SI NO LO HACE, PUEDE OCASIONAR DAÑO AL EQUIPO.

TRANE  
2313-1813  
2313-1815  
1 OF 1  
B

POWER SCHEMATIC - 90-130 TON  
W/ SUPPLY FAN VARIABLE FREQUENCY DRIVE  
SCHEMATIC 1 OF 5

DATE: 11/12/12  
DRAWN BY: T. THOMAS  
CHECKED BY: T. THOMAS  
REVISED DATE: 11/12/12  
REVISED DATE: 11/12/12  
SCALE: 1:1  
PROJECT: 2313-052-A  
CADD SYSTEM USED: PRO/ADAM