

- UNLESS OTHERWISE NOTED. ALL SWITCHES ARE SHOWN AT 25°C (77°F) AT ATMOSPHERIC PRESSURE. AT 50% RELATIVE HUMIDITY WITH ALL UTILITIES TURNED OFF AND AFTER A NORMAL SHUTDOWN HAS OCCURRED.
- 2. DASHED LINES INDICATE RECOMMENDED FIELD WIRING BY OTHERS. DASHED LINE ENCLOSURES AND/OR DASHED DEVICE OUTLINES INDICATE COMPONENTS PROVIDED BY THE FIELD. PHANTOM LINE ENCLOSURES INDICATE ALTERNATE CIRCUITRY OR AVAILABLE SALES OPTIONS.
- NUMBERS ALONG THE RIGHT SIDE OF THE SCHEMATIC DESIGNATE THE LOCATION OF CONTACTS BY LINE NUMBER. AN UNDERLINED NUMBER INDICATES A NORMALLY CLOSED CONTACT.
- THREE-PHASE MOTORS ARE PROTECTED UNDER PRIMARY SINGLE PHASING CONDITIONS. ALL MOTORS HAVE INTERNAL OVERLOAD PROTECTION AND COMPRESSORS HAVE INTERNAL THERMAL PROTECTION.
- CONNECTIONS SHOWN ARE FOR 230V/60HZ/1PH UNITS. WHEN 208V/60HZ/1PH OPERATION IS REQUIRED. MOVE WIRE W9 (BLK) FROM THE 230V TERMINAL ON TNS1 TO THE 208V TERMINAL.
- CONNECTIONS SHOWN ARE FOR LOW SPEED OPERATION. WHEN HIGH SPEED OPERATION IS REQUIRED. MOVE WIRE W7 FROM FTB-C TO FTB-D.
- CONNECTIONS SHOWN ARE FOR 4 AND 5 TON UNITS. FOR 3 TON UNITS (AND BELOW), THERE ARE NO FAN RELAY (F) JUMPERS FROM PIN 3 TO PIN 6 OR FROM PIN 1 TO PIN 4.

REF	DESCRIPTION	LINE		
CC1	C1 COMPRESSOR CONTACTOR			
CCH	CCH CRANKCASE HEATER			
CF1	OD MOTOR CAPACITOR	30		
CF2	ID MOTOR CAPACITOR	12		
CPR1	COMPRESSOR	24		
CR	CPR RUN CAPACITOR	24		
CS	CPR START CAPACITOR	19		
CSR	CPR START RELAY	19		
CTL	COIL TEMP LIMIT SWITCH	27		
F	FAN RELAY	9.10		
FTB	FAN TERMINAL BLOCK	8.10.12		
IDM	ID FAN MOTOR	10		
ODM	OD FAN MOTOR	31		
R2	CPR START RESISTOR	20		
TNS1	LOW VOLTAGE TRANSFORMER	45		

COLOR	ABBR	COLOR	ABBR
BLACK	BLK	ORANGE	ORG
BLUE	BLU	RED	RED
BROW N	BRN	VIOLET (PURPLE)	V10
GRAY (SLATE)	GRA	WHITE	WHT
GREEN/YELLOW	G/Y	YELLOW	YEL

## **MARNING**

2-

3-4-

6-7-

8-9-

10-

11-

12-

13-14-15-

16-

17-18-

19-20-21-22-

23-

24-

25-26-

27-28-29-

30-

31-

32-33-34-35-36-37-38-39-40-41-42-

43-44-

45-46-

47-48-49-

50-51-

52-53-

54-

55-56-

57-

58-

59-60-

61-62-

63-

64-65-66-67-68-69-70-71-

72-

73-

74-

75-76-

77-

78-

HAZARDOUS VOLTAGE!

DISCONNECT ALL ELECTRIC POWER INCLUDING REMOTE DISCONNECTS AND FOLLOW LOCK OUT AND TAG PROCEDURES BEFORE SERVICING. INSURE THAT ALL MOTOR CAPACITORS HAVE DISCHARGED STORED VOLTAGE. UNITS WITH VARIABLE SPEED DRIVE. REFER TO DRIVE INSTRUCTIONS FOR CAPACITOR DISCHARGE.

FAILURE TO DO THE ABOVE COULD RESULT IN DEATH OR SERIOUS INJURY.

## **AVERTISSEMENT**

TENSION DANGEREUSE!

COUPER TOUTES LES TENSIONS ET OUVRIR LES SECTIONNEURS À DISTANCE. PUIS SUIVRE LES PROCÉDURES DE VERROUILLAGE ET DES ÉTIQUETTES AVANT TOUTE INTERVENTION. VÉRIFIER QUE TOUS LES CONDENSATEURS DES MOTEURS SONT DÉCHARGÉS. DANS LE CAS D'UNITÉS COMPORTANT DES ENTRAÎNEMENTS À VITESSE VARAIBLE. SE REPORTER AUX INSTRUCTIONS DE L'ENTRAÎNEMENT POUR DÉCHARGER LES CONDENSATEURS.

NE PAS RESPECTER CES MESURES DE PRÉCAUTION PEUT ENTRA ÎNER DES BLESSURES GRAVES POUVANT ÊTRE MORTELLES.

## **CAUTION**

USE COPPER CONDUCTORS ONLY! UNIT TERMINALS ARE NOT DESIGNED TO ACCEPT OTHER TYPES OF CONDUCTORS. FAILURE TO DO SO MAY CAUSE DAMAGE TO THE EQUIPMENT.

## **IMPORTANT**

DO NOT ENERGIZE UNIT UNTIL CHECK-OUT AND START-UP PROCEDURE HAS BEEN COMPLETED.

10:	NOT SCALE PRINT	8v:K.Vickmark ⊚⊅	DISCLOSED TO OUTSIDE PARTIES WITHOUT THE BRITTEN CONSENT OF TRANS	A DIVISION OF ANGELCAN STANDARD INC. ALL RIGHTS RESERVED
© 	THIRD ANGLE	© DATE: 22-Aug-00	PITHOUT THE WRITTEN	ARD INC.
	3-5 TON, 230V-1PH PWR	POWER - COOL ONLY	DIAGRAM	4366-1019

TI 👼

DRAWN E